CONTRONETIX LINE INTERACTIVE UPS



Built-in AVR Function



Universal Output Sockets



220~240VAC



Overload & Overcharge Protection



**OUPS V1200** 

V1200
1200VA
Single phase
220~240VAC
50/60Hz (±10%)
0.6
Simulated sine wave at nominal voltage ±10%
50/60Hz ±1Hz
Typical 2-6 ms, 10ms max.
Automatically increase/decrease output voltage by -13% to +10% if the nominal input voltage fluctuates from -26% to +22%
12V/7Ah x 2
6-8 hours recover to 90% capacity
Overload and overcharge protection
Beeping every 10 seconds
Beeping every 1 second
Beeping every 0.5 second
Continuously beeping sound
Approx. 7.8

